

WriteLog on the air Keyboard Shortcuts V10.40J

| | | | |
|--|---------------------------------------|---|---|
| Log window..... | CTL-N | QSO Entry window..... | CTL-P |
| enter with cursor in Edit mode | CTL-Y | Abort message in progress | Escape or Shift-Home or CTL-C* |
| (use arrow keys to move to desired QSO and field) | | | |
| Delete QSO | Right-Click QSO | Band: next lower freq | ALT-F1 |
| Ignore QSO for scoring | highlight QSO & type X | next higher freq | ALT-F2 |
| restore: | highlight QSO & type Space | Callsigns, queue of RTTY received | ALT-C |
| QSL, mark to send | Right-Click QSO | CQ message | F11 or F1* or Enter (cursor in empty callsign field) |
| QSO, correcting: | double-click field to open QSO Edit | Cursor, move to | |
| save change | Enter | end of current field | End |
| undo change before saving | CTL-Z | end of last field | CTL-E ("end") |
| window close | double-click on background | left one character | ← or CTL-B ("backward") |
| Scroll: down one line..... | CTL-↓ | next field | Space or Tab |
| down one page..... | Page Down | previous field | Shift-Tab |
| up one line..... | CTL-↑ | right one character | → or CTL-F ("forward") |
| up one page..... | Page Up | start of current field | Home |
| Messages | <i>End all messages with a space.</i> | start of first (leftmost) field | CTL-A |
| Function keys: program with "Setup CW/RTTY Messages" pull-down menu or Shift-Fn (voice). (Message contents vary according to operator taste and contest requirements.) | | CW: speed: faster ... ALT-F10 or Page-Up; ALT-Shift-F10† slower .. ALT-F9 or Page-Down; ALT-Shift-F9† weight: heavier .. Shift-PgUp lighter .. Shift-PgDn | |
| Repeat field in exchange | Click button over field | Delete character | |
| To program: | Shift-Click button over field | previous character | Backspace |
| Special message parameters: | | under cursor | CTL-D or Delete |
| CW speed up / down | < or > | Delete in the current field | |
| CW prosigns: AA + BT - | | entire field | CTL-W ("wipe") |
| AR @ KN # | | to right of cursor | CTL-K ("kill") |
| AS] SK [| | Delete QSO | ALT-W ("wipe") or CTL-Backspace or F11* |
| error Delete | | Delete QSO number: | Clear the callsign field, or CTL-A & Backspace |
| Field <i>n</i> from QSO Entry window | %Fn | Enter QSO: | |
| Hello name (extract from "Hi" file) | %H | Send TU msg (with corrected call if changed) | |
| His call | %D or | + or Enter (cursor not in callsign field) | |
| If cursor in call field, wait until user finishes typing call before continuing | %C | Silent logging | Shift-Enter or CTL-Enter |
| Insert data from user (prompt now) | %I | Frequency: go to | type freq in call field, Enter |
| Memory <i>n</i> inserted here (1-11, 21-31=shift) | %Mnn | Split transmit freq | - |
| My number..... | %n, n=1 to 5 (min # digits) | Frequency scratchpad memory | |
| Previous QSO's exchange field <i>n</i> | %Pn | toggle to/from | CTL-Tab |
| Previous QSO's serial number..... | %PO | exchange memory with current QSO | Shift-click |
| QSO before message | %B text %B | move between entries | Tab, Shift-Tab |
| RTTY Return key | %R | set # of scratchpad entries | Right-click |
| RTTY end of transmission..... | %E | Gab, send a network | ALT-G |
| Speed increase or decrease | < or > | Go to QSO | enter call fragment (*, ? wildcards) or enter log sequence number |
| Time of day..... | %T | then | CTL-G ("go") |
| Rate window: Select single- or all-band rate....Right-click | | Headphone, latch to non-xmtg radio | CTL-X** |
| RTTY window | <i>Right-click for other actions</i> | His Call + Exchange / QSO B4 | F10 or Insert or Enter (cursor in non-empty callsign field) |
| Callsigns, queue of RTTY received | ALT-C | Keyboard sending | Alt-K |
| Letters case, shift receive to..... | ALT-L | Mode, changing | CTL-F1 or CTL-F2 |
| Move selected characters to QSO Entry window | | Note, create a | ALT-N |
| Left click | | QTC: | |
| Invert Ltrs/Figs..... | Shift-Left click | receive QTC window | ALT-R |
| Only highlighted part of call..... | CTL-Left click | request fill on QTC #n | ALT-n |
| | | send QTC window | ALT-S |
| | | Radio, switching: | |
| | | activate radio with keybd focus for xmit | CTL-R |
| | | keybd entry only | Shift-↑ or Shift-↓ |
| | | keybd entry and transmit | ↑ or ↓ |
| | | transmit only | CTL-↑ or CTL-↓ |
| | | Received calls (RTTY only) | ALT-C |
| | | Repeating CQs | ALT-T ("timed repeat") |
| | | RIT, clear the offset | * |
| | | RTTY receive: shift to Letters case | ALT-L |
| | | Spot: announce | CTL-T or ALT-F3 |
| | | Return o 0.00 kHz | F12 |

WriteLog on the air Keyboard Shortcuts V10.40J

| <u>Key</u> | <u>(plain)</u> | <u>Shift</u> | <u>CTL-key</u> | <u>ALT-key</u> | <u>ALT-Shift-key</u> |
|-------------------|--|---------------------|--|--|-----------------------------|
| A | a | A | <i>QSO Entry:</i> move cursor to start of first field. | | |
| B | b | B | <i>QSO Entry:</i> move cursor left 1 char. | | |
| C | c | C | Abort message in progress. | <i>RTTY or QSO Entry:</i> display queue of received calls. | |
| D | d | D | <i>QSO Entry:</i> delete char under cursor. | | |
| E | e | E | <i>QSO Entry:</i> move cursor to end of last field. | | |
| F | f | F | <i>QSO Entry:</i> move cursor right 1 char. | | |
| G | g | G | <i>QSO Entry:</i> if call, call fragment with wildcard, or QSO # is in callsign field, jump to QSO in Log. | <i>QSO Entry:</i> send network gab msg. | |
| H | h | H | | | |
| I | i | I | | | |
| J | j | J | | | |
| K | k | K | <i>QSO Entry:</i> delete all to right of cursor. | <i>QSO Entry:</i> toggle CW keyboard sending window open & closed. | |
| L | l | L | | <i>RTT or QSO EntryY:</i> force rcvr to ltrs case. | |
| M | m | M | | | |
| N | n | N | <i>Focus to Log window.</i> | <i>QSO Entry:</i> create a note. | |
| O | o | O | | | |
| P | p | P | <i>Focus to QSO Entry window.</i> | | |
| Q | q | Q | | | |
| R | r | R | <i>QSO Entry:</i> move xmit focus to radio with keyboard focus. | <i>QSO Entry:</i> open QTC rcv window. | |
| S | s | S | | <i>QSO Entry:</i> open QTC xmit window. | |
| T | t | T | <i>QSO Entry:</i> announce last QSO to packet. | <i>QSO Entry:</i> start or stop timed CQs. | |
| U | u | U | | | |
| V | v | V | | | |
| W | w | W | <i>QSO Entry:</i> delete field's contents. | <i>QSO Entry:</i> erase the form. | |
| X | x or <i>Log with QSO highlighted:</i> mark QSO unclaimed. | X | <i>QSO Entry:</i> toggle headphone latch (W5XD Multikeyer+). | | |
| Y | y | Y | <i>Focus to Log with cursor in Edit mode</i> | | |
| Z | z | Z | <i>Log, editing a QSO:</i> undo the change. | | |
| 1 | 1 | | | <i>QSO Entry:</i> request repeat QTC #1. | |
| 2 | 2 | | | <i>QSO Entry:</i> request repeat QTC #2. | |
| 3 | 3 | | | <i>QSO Entry:</i> request repeat QTC #3. | |
| 4 | 4 | | | <i>QSO Entry:</i> request repeat QTC #4. | |
| 5 | 5 | | | <i>QSO Entry:</i> request repeat QTC #5. | |
| 6 | 6 | | | <i>QSO Entry:</i> request | |

WriteLog on the air Keyboard Shortcuts V10.40J

| <u>Key</u> | <u>(plain)</u> | <u>Shift</u> | <u>CTL-key</u> | <u>ALT-key</u> | <u>ALT-Shift-key</u> |
|-------------------|---|---|---|---|--|
| 7 | 7 | | | repeat QTC #6. <i>QSO Entry:</i> request repeat QTC #7. | |
| 8 | 8 | | | <i>QSO Entry:</i> request repeat QTC #8. | |
| 9 | 9 | | | <i>QSO Entry:</i> request repeat QTC #9. | |
| 0 | 0 | | | <i>QSO Entry:</i> request repeat QTC #10. | |
| F1 | Open help ¹ or Send message ² | Send message ² | <i>QSO Entry:</i> next mode. | <i>QSO Entry:</i> next lower freq band. | |
| F2 | Send message | Send message | <i>QSO Entry:</i> previous mode. | <i>QSO Entry:</i> next higher freq band. | |
| F3 | Send message | Send message | | <i>QSO Entry:</i> announce last QSO to packet. | |
| F4 | Send message | Send message | | | |
| F5 | Send message | Send message | | | |
| F6 | Send message | Send message | | | |
| F7 | Send message | Send message | | | |
| F8 | Send message | Send message | | | |
| F9 | Send message | Send message | | <i>QSO Entry:</i> CW speed down on radio with keyboard focus. | <i>QSO Entry:</i> CW speed down on radio without keyboard focus. |
| F10 | Send message | Send message | | <i>QSO Entry:</i> CW speed up on radio with keyboard focus. | <i>QSO Entry:</i> CW speed up on radio without keyboard focus. |
| F11 | Send message ¹ or <i>QSO Entry:</i> erase the form. ² | Send message ¹ | | | |
| F12 | <i>QSO Entry:</i> return to previous freq (after grabbing spot). | | | | |
| Back-space | <i>QSO Entry:</i> delete char before cursor; if at start of first field, erase the QSO sequence number. | | <i>QSO Entry:</i> erase the form. | | |
| Delete | <i>QSO Entry:</i> delete char under cursor; or <i>CW message:</i> error prosign. | | | | |
| End | <i>QSO Entry:</i> Move cursor to end of field. | | | | |
| Enter | <i>QSO Entry, cursor in empty callsign field:</i> send CQ message; or <i>QSO Entry, cursor in non-empty callsign field:</i> send his call + exchange msg; or <i>QSO Entry, cursor not in callsign field:</i> send TU message & log QSO. | <i>QSO Entry:</i> log QSO silently (no TU). | <i>QSO Entry:</i> log QSO silently (no TU). | | |
| Esc | Abort message in progress. | | | | |
| Home | <i>QSO Entry:</i> move cursor to start of field | Abort message in progress. | | | |
| Insert | <i>QSO Entry:</i> send his call + exchange msg. | | | | |

¹ CtCompatibleAccel=NO

² CtCompatibleAccel=YES

WriteLog on the air Keyboard Shortcuts V10.40J

| Key | (plain) | Shift | CTL-key | ALT-key | ALT-Shift-key |
|------------------|---|---|--|----------------|----------------------|
| Page Down | <i>Log</i> : page down one screen; or <i>QSO Entry</i> : CW speed down. | <i>QSO Entry</i> : decrease CW weight. | | | |
| Page Up | <i>Log</i> : page up one screen; or <i>QSO Entry</i> : CW speed up. | <i>QSO Entry</i> : increase CW weight. | | | |
| Space | <i>Log with QSO highlighted</i> : mark QSO claimed; or <i>QSO Entry</i> : next field (skipping Tab-only fields). | <i>QSO entry</i> : previous field (skipping Tab-only fields). | | | |
| Tab | <i>QSO Entry</i> : next field; or <i>S&P Memory</i> : next memory | <i>QSO Entry</i> : previous field; or <i>S&P Memory</i> : previous memory. | <i>QSO Entry or S&P Memories</i> : toggle between QSO Entry and S&P Memory windows. | | |
| ↓ | <i>QSO Entry</i> : move keyboard & xmit focus to next radio down. | <i>QSO Entry</i> : move keyboard focus only to next radio down. | <i>Log</i> : scroll down one line; or <i>QSO Entry</i> : move xmit focus only to next radio down. | | |
| ↑ | <i>QSO Entry</i> : move keyboard & xmit focus to next radio up. | <i>QSO Entry</i> : move keyboard focus only to next radio up. | <i>Log</i> : scroll up one line; or <i>QSO Entry</i> : move xmit focus only to next radio up. | | |
| → | <i>QSO Entry</i> : move cursor right 1 char. | | | | |
| ← | <i>QSO Entry</i> : move cursor left 1 char. | | | | |
| ! | | | | | |
| @ | <i>CW message</i> : AR | | | | |
| # | <i>CW message</i> : KN | | | | |
| \$ | | | | | |
| % | | | | | |
| ^ | | | | | |
| & | | | | | |
| * | <i>QSO Entry (numeric pad only)</i> : zero RIT. | | | | |
| (| | | | | |
|) | | | | | |
| - | | | | | |
| - | <i>CW message</i> : BT; or <i>QSO Entry</i> : open split freq pop-up window. | | | | |
| + | <i>CW message</i> : AA; or <i>QSO Entry</i> : send TU message & log QSO. | | | | |
| = | | | | | |
| { | | | | | |
| } | | | | | |
| [| <i>CW message</i> : SK | | | | |
|] | <i>CW message</i> : AS | | | | |
| | | | | | |
| \ | | | | | |
| / | | | | | |
| : | | | | | |
| ; | | | | | |
| " | | | | | |
| . | | | | | |
| < | <i>CW message</i> : speed | | | | |

WriteLog on the air Keyboard Shortcuts V10.40J

| Key | (plain) | Shift | CTL-key | ALT-key | ALT-Shift-key |
|--------------------|---|--------------|--|----------------|----------------------|
| | up. | | | | |
| > | <i>CW message:</i> speed down. | | | | |
| ? | | | | | |
| , | | | | | |
| . | | | | | |
| Right click | <i>S&P Memory:</i> set number of memories. <i>Rate:</i> configure rate algorithm. | | | | |
| Left click | <i>RTTY:</i> move selected chars to QSO Entry callsign field. <i>S&P Memory:</i> Exchange this memory with current freq & callsign in QSO Entry; or <i>RTTY:</i> invert letters/figures case and move selected chars to QSO Entry callsign field. | | <i>RTTY:</i> only move highlighted characters of call to QSO Entry callsign field. | | |